



*** Default Settings**

ASYN1	J 9	J 10	ASYN2	J 7	J 8	Printer Mode	J 13	J 14	Printer Port	J 11	J 12
*COM1 (3F8)	2 - 3	1 - 2	*COM2 (2F8)	2 - 3	1 - 2	* EPP/ECP	1 - 2	2 - 3	* LPT1 (378)	1 - 2	2 - 3
COM3 (3E8)	1 - 2	2 - 3	COM3 (3E8)	2 - 3	2 - 3	EPP	2 - 3	1 - 2	LPT2 (278)	2 - 3	1 - 2
COM4 (2E8)	2 - 3	2 - 3	COM4 (2E8)	1 - 2	2 - 3	SPP	2 - 3	2 - 3	LPT3 (3BC)	2 - 3	2 - 3
Disable	1 - 2	1 - 2	Disable	1 - 2	1 - 2	Reserved	1 - 2	1 - 2	Disable	1 - 2	1 - 2

JMP	Function	1 - 2/ON	2 - 3/OFF
J2	ASYN2 Mode	* Serial	IrDA
J3	FDD A/B Swap	A/B Swap	* Normal
J4	FDC Enable	Disabled	* Enabled
J5	IDE Address	* Primary	Secondary
J6	IDE Enable	Disabled	* Enabled
J15	Game Port	* Enabled	Disabled
J17	IDE IRQ	* IRQ 14	IRQ15

ESIO-V2.1